

# 大同大學 九十四 學年度 碩士班入學考 試題

考試科目:電磁學 所別:通訊工程研究所 第1/1頁

註:本次考試不可以參考自己的書籍及筆記; 不可以使用字典; 可以使用計算器。

1. A circular disk of radius  $b$  and thickness  $t$  carries a current in a circular direction about the center. A cylindrical coordinate system has the origin at the center of the disk and has the  $z$  axis coinciding with the axis of symmetry of the disk. The current density in the disk is  $\vec{J} = kr\vec{a}_\phi$  A/m<sup>2</sup>, where  $k$  is a real constant greater than zero. Derive a formula for the magnetic intensity  $\vec{H}$  at the center of the disk, assuming that the thickness  $t$  is very small compared with  $b$ . (25%).

2. Briefly answer the following questions: (25%)

- The divergence of a vector field  $\vec{F}$  is defined as  $\nabla \cdot \vec{F} = \lim_{\Delta v \rightarrow 0} \frac{\oint_S \vec{F} \cdot d\vec{s}}{\Delta v}$ , explain it.
- What is the difference between *convection current* and *conduction current*?
- Explain the *Gaussian Surface* in electrostatics.
- Why must the electric field lines point directly away from or toward the conductor surface?
- Make comments on the term  $\frac{\partial \vec{D}}{\partial t}$  in Ampère law of Maxwell's equations, where  $\vec{D}$  is the electric flux density vector.

3. A uniform sinusoidal plane wave in air with the following phasor expression for electric intensity

$$\vec{E}_i(x, z) = \vec{a}_y 10 e^{-j(6x+8z)} \quad (\text{V/m})$$

is incident on a perfectly conducting plane at  $z = 0$ .

- Find the frequency and wavelength of the wave.
  - Write the instantaneous expressions for  $\vec{E}_i(x, z; t)$  and  $\vec{H}_i(x, z; t)$ , using a cosine reference.
  - Determine the angle of incidence
  - Find  $\vec{E}_r(x, z)$  and  $\vec{H}_r(x, z)$  of the reflected wave
  - Find  $\vec{E}_1(x, z)$  and  $\vec{H}_1(x, z)$  of the total field
4. An antenna is fed by a  $70\Omega$  lossless line with a quarter-wave length. With what input impedance must this antenna be designed to yield a  $50\Omega$  input impedance of this feeding line? (25%)