

65

大同工學院 八十八 學年度研究所招生入學考試試題

考試科目：通訊原理

所別：通訊工程研究所

第1/1頁

註：本次考試不可以參考自己的書籍及筆記； 不可以使用字典； 可以使用計算器。

- A sinusoidal signal of frequency 1 Hz is to be sampled periodically.
 - Find the maximum allowable time interval between samples.(5%)
 - The samples are spaced $\frac{2}{3}$ sec apart. Show graphically the spectrum of the sampled signal.(5%)
- For a signal $f(t)=A\cos(\omega t+\theta)$
 - Find the autocorrelation function of $f(t)$.(5%)
 - Find the power spectral density of $f(t)$.(5%)
 - Find the power of $f(t)$. (5%)

- A system has the transfer function

$$H(f) = \frac{3 + j2\pi f}{10 + j2\pi f}$$

Determine whether the system is distortionless or not.(10%)

- Consider an FM modulator with output

$$y(t) = 50 \cos[2\pi(1000)t + 2\pi f_d \int m(\tau) d\tau]$$

Table of Bessel Function $J_n(\beta)$

n	$\beta=3.0$	$\beta=5.0$	$\beta=7.0$	$\beta=8.0$
0	-0.260	-0.178	0.300	0.172
1	0.339	-0.328	-0.005	0.235
2	0.486	0.047	-0.301	-0.113
3	0.309	0.365	-0.168	-0.291
4	0.132	0.391	0.158	-0.105

The modulator operates with $f_d=6$ and has the input message signal

$$m(t) = 5 \cos(12\pi t)$$

The modulator is followed by a bandpass filter with a center frequency of 1000 Hz and a bandwidth of 56 Hz.

- Determine the peak frequency deviation and modulation index.(5%)
 - Determine the power at the filter output.(10%)
- A delta modulator has the message signal

$$m(t) = 9\sin(20\pi t) + 5\sin(40\pi t)$$

Determine the minimum sampling frequency required to prevent slope overload, assuming that the impulse weights δ are 0.05π .(10%)
 - Please calculate the information capacity (in bits) of a 450-page book, assuming 500 words per page, each word containing five symbols chosen at random from a 37-ary alphabet (26 letters, 10 digits, and a blank space).(10%)
 - An M -ary communication system transmits at a rate of 1000 symbols per second.
 - What is the baud rate?(5%)
 - What is the equivalent bit rate in bits per second for $M=64$?(5%)
 - If $M=2$, what kinds of modulation can achieve the best performance (error probabilities), PSK, ASK, or FSK?(5%)
 - Let $\mathbf{x}_m = (x_{m1}, x_{m2}, \dots, x_{mN})$, $m=1,2,\dots, M$, be a set of M binary sequences each of length N . Message m is represented by sequence \mathbf{x}_m . One of the sequences is transmitted over the binary symmetric channel. Let $\mathbf{y} = (y_1, y_2, \dots, y_N)$ represent the received binary sequence. For a binary symmetric channel, the conditional error probability for the n^{th} symbol is p if $y_n \neq x_{mn}$ and is $(1-p)$ if $y_n = x_{mn}$. Let d_m be the number of places \mathbf{x}_m differs from \mathbf{y} . The receiver determines which message was transmitted by observing \mathbf{y} . What is the maximum likelihood decision rule?(15%)