

大同大學 九十六學年度 碩士班入學考 試題

考試科目: 電磁學 所別: 通訊工程研究所 第1/1頁

註: 本次考試 不可以 參考自己的書籍及筆記; 不可以 使用字典; 可以 使用計算器。

1. A $50 - \Omega$ lossless line is to be matched to an antenna with $Z_L = (80 + j25)\Omega$ using a shorted stub. Use the Smith Chart to determine the stub length and distance between the antenna and stub. [Hint: 共有二組解; 利用提供的 **Smith Chart** 作計算, 只在答案卷上說明並給與答案; **Smith Chart** 不評分, 繳不繳回, 與題目卷一致, 依考場規定] (25%).
2. Briefly answer the following questions: (30%)
 - a. Explain *Stokes's theorem* in vector operation
 - b. What is the relationship between VSWR and reflection coefficient in transmission line? Explain.
 - c. What is the *dielectric constant* of materials?
 - d. Explain "eddy current"
 - e. Explain the characteristics of a *plane wave* in free space.
3. The instantaneous expression for the magnetic field intensity of a uniform plane wave propagating in the + y direction in air is given by

$$\vec{H} = \vec{a}_z 4 \times 10^{-6} \cos\left(10^7 \pi t - k_0 y + \frac{\pi}{4}\right) A/m$$

- a) Determine k_0 and the location where H_z vanishes at $t = 3$ (ms).
 - b) Write the instantaneous expression for \vec{E} . (20%)
4. (1) For the vector field $\vec{A} = 10e^{-r} \vec{a}_r - 3z\vec{a}_z$, verify the divergence theorem for the cylindrical region enclosed by $r = 2$, $z = 0$, and $z = 4$ (10%)
 - (2) $f = xy^2z^3$, Find ∇f (5%)
 - (3) Given $V = 5e^{-r} \cos \phi$, find $\nabla^2 V$. (5%)
 - (4) $\vec{A} = y\vec{a}_x + xyz\vec{a}_z$, determine if it is solenoidal, conservative, or both. (5%)

The Complete Smith Chart

Black Magic Design

