

大同大學 99 學年度研究所碩士班入學考試試題

考試科目：電磁學

所別：通訊工程研究所

第1/1頁

註：本次考試 不可以參考自己的書籍及筆記； 不可以使用字典； 不可以使用計算器。

1. Prove that a maximum power is transferred from a voltage source with an internal impedance Z_g to a load impedance Z_L over a lossless transmission line when $Z_i = Z_g^*$, where Z_i is the impedance looking into the loaded line. What is the maximum power-transfer efficiency? (25%)
2. Explain the following terms: a) Hysteresis loop, b) Gauss's Law, c) Helmholtz coils, d) Magnetic Vector Potential Function, and e) Stokes's theorem (25%)
3. The distance between a transmitting and a receiving antenna in free space is d . If P_t and P_r are respectively the power radiated by the transmitting antenna and the power received in the load of the receiving antenna, show that $P_r / P_t = A_t A_r / (d\lambda)^2$, where A_t and A_r are respectively the maximum effective aperture of the transmitting and the receiving antenna and λ is the operating wavelength. (25%)
4. Explain the following terms: a) VSWR, b) microstrip line, c) Poynting theorem, d) cut off frequency, and e) dispersion (25%)